


POS Printer
SP712/742

Installation Manual

for WindowsVista




1. Installing the Windows Vista Driver


To use the SP700 under the Windows Vista environment, the proper driver must be installed in advance. Follow the directions below to install the driver.

Note: Set the accessory CD-ROM into your PC prior to connecting the printer.
Follow the directions below.
Turn on the printer after completing step (2) below.

- (1) Set the printer's accessory CD-ROM into the PC. The following screen is displayed. Click [Open folder to view files].



- (2) Create a new folder anywhere that is convenient for you, for example "desktop/SP700" and copy the files and folders in <WinVista/Driver/SP712_742_PrinterDriver_Vista> into that new folder. (When copied, the compressed data will be expanded for use.)



Note: The procedures described below vary depending upon the type of interface you have. Use the procedures that are provided for the interface type you use.


1.1 For USB Interfaces (From Page 3)

1.2 For Other Interfaces (From Page 7)


1.1 For USB Interfaces

- (1) Turn on the power to your SP700.


The screen below is displayed. Click [Locate and install driver software (recommended)].




- (2) The User Account Control screen is displayed. Click [Continue].
- (3) The driver you copied above will be used now.
Click [I don't have the disc. Show me other options.]




- (4) Click [Browse my computer for driver software (advanced).]




- (5) Click [Browse] and specify the location of the folder created on the desktop ("desktop"/SP700). Then, click [Next].





- (6) Run the installation program.



- (7) When the installation is successfully completed, the screen below is displayed. Click [Close (C)].



- (8) Select [Settings] - [Printers] from the Windows Start button to open the Printer Settings screen.
If the printers Star SP700 Cutter(SP742) or Star SP700 TearBar(SP712) in the folder are displayed, the installation has been completed successfully.




Note: The folder and file created on your desktop for the installation are no longer necessary and can be deleted.


1.2 For Other Interfaces

Port settings are not necessary if using the SP700 by connecting with a TCP/IP interface cable.


- (1) Select [Settings] - [Printers] from the Windows Start menu.




- (2) The Printers Setting screen is displayed. Click [Add a printer].




- (3) Either the Local Printer or Network Printer Selection Screen is displayed.
Click [Add a local printer].





- (4) The Local Printer Selection Screen is displayed. Click the port to use, then click [Next].




- (5) The Choose a Printer screen is displayed. Click [Have Disk].




- (6) Click [Browse] in the screen to install from a floppy disk to call up the file selection menu. Specify <smjs718w.inf> from the folder you created on the desktop ("desktop"/SP700), then click [Open].




(7) Click [OK].




(8) The printer driver installation screen is displayed. Select the printer to use, and click [Next].



- (9) After installation of the printer driver, set the name of the printer to use in Windows.
Click on the printer name to change printers. You can specify the currently installed printer as the one to use normally. Click [Next] to start the installation.




- (10) The User Account Control screen is displayed. Click [Next].
(11) Run the installation program.




(12) When the installation is completed successfully, the screen below is displayed.

To run a print test, click [Finish]. the Installation screen is displayed.



(13) Select [Settings] - [Printers] to call up the Printer Settings screen.

If the printers you installed Star SP700 Cutter (SP742) or Star SP700 Tear Bar (SP712) are displayed, the installation has been successful.



Note: The folder and file created on your desktop for the installation are no longer necessary and can be deleted.